

MX - EC136C Range

20Watt LED Weatherproof Batten

Model Number	MXA-EC136C	MX-EEC136c
Functions		
Standard	yes	yes
Emergency	no	yes
Micro wave sensor switch	no	no
Emergency function and micro wave switch	no	no



SPECIFICATIONS

Power consumption	18.5 watts
Lumen Flux	1600lm
Dimensions	L 1274mm x W90mm x H 90mm
LED Luminous Efficiency	100 lumens / watt
Power Factor	>0.95
Operating Temperature	25C
Input Voltage	220 - 240 Volts, 50Hz
IP Rating	IP65
Colour Temperature	2700 - 3300 kelvin 3800 - 4600 kelvin 5500 - 6500 kelvin
Colour Index	>Ra80
Emergency Classification	CO-D63....21mt spacing's Classification in accordance with AS2293.3 D90-D40....18mt spacing's
Certificate	Certificate of Suitability CS10275N IEC 60598-2-22 2014 N30442
Certificate	CE & ROHS & SAA
Life Expectancy	50,000+ Hrs
Warranty	3 years

This product is eligible for the NSW Energy Savings Scheme

*Under emergency mode the light will generate 5watts

*Microwave Sensor will automatically dim the fitting to 25% of output wattage.

*all Microwave and timer setting are automatically set at the factory but instructions to reset these if necessary can be obtained by contacting Matrix LED